

NEPA GROUND SQUARE 3 INOX

INSTALLATION INSTRUCTIONS

1 Unscrew the (4) screws.

2 Loosen the screws and remove the inner flange

3 Remove the fixture from the box.

4 Unscrew the (4) screws

5 Pass the cable through the cable gland of the box.

6 Make wiring connections.

7 Insert box in the ground hole, 2mm above ground surface

8 Insert the fixture in the box. Tighten the (4) screws,

9 Fit the glass, the flange and tighten the screws.


10 Fit the the cap. Tighten the (4) screws.

USER INSTRUCTIONS

- The installation of the unit must be done by a qualified electrician.
- The unit must be earthed in case an earth connecting point exists.
- Ensure that the mains is switched off during servicing.
- Do not use bulb(s) bigger than the indicated on units name-plate or packaging.
- Ensure that after the installation, the unit is properly fixed and the cable clamps (if exist) are well tightened.
- Manufacturer will not accept liability for injury or damage resulting from incorrect use or installation
- The unit is not intended to operate in loop connection.
- Wall plugs and terminals are not included.
- LED modules are replaced only by the manufacturer.


CAUTION

Replace any cracked shield



CAUTION

Wear anti-static gloves before you touch LED systems



UPDATE DEC 2020